

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

AMENDMENTS TO THE CLAIMS:

This listing of claims will replace all prior versions and listings of claims in the application:

1. (Currently Amended) A semiconductor testing apparatus for testing semiconductor devices, configured to feed back data of returned samples which have been shipped as good samples, but returned from a user to a ~~manufacture~~ manufacturer as faulty samples so as to improve testing performance, the semiconductor testing apparatus comprising:

an IDDQ measuring circuit configured to measure current data of good samples and the samples ~~returned~~ returned by the user, by supplying test vector data to the good and returned samples;

a determination circuit configured to determine a range of pass/fail decision criteria and effective address pairs for testing target semiconductor devices based upon the measured current data,

wherein the IDDQ measuring circuit tests the target semiconductor devices by applying the test vector data for the effective address pairs.

2. (Previously Presented) The apparatus of claim 1 wherein the determination circuit comprises:

a changing rate calculation circuit configured to select a plurality of address pairs from the test vector data, to supply the address pairs to the good samples and the returned samples, to measure current-values of the good

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

samples and returned samples, and to calculate changing rates of each of the good samples and returned samples;

a range criteria determination circuit configured to determine the range of pass/fail decision criteria by using the changing rates of each of the good samples;

a comparing circuit configured to compare the changing rates of each of the returned samples to the range of pass/fail decision criteria, and to determine whether the changing rates of each of the returned samples fall outside of the range of pass/fail decision criteria; and

an effective address pair determination circuit configured to determine the changing rate falling out of the range of pass/fail decision criteria, and to select an address pair which makes the returned samples to provide the changing rate falling outside of the range of the pass/fail decision criteria as the effective address pair.

3. (Previously Presented) The apparatus of claim 1, wherein the IDDQ measuring circuit comprises:

a tester configured to: acquire the effective address pair, supply the test data corresponding to the effective address pair to the target semiconductor device, measure current-value output of the target semiconductor device, and calculate changing rates of the target semiconductor device; and

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

a decision circuit configured to determine a changing rate falling outside of the range of pass/fail decision criteria.

4. (Previously Presented) The apparatus of claim 1 further comprising a display configured to display the changing rate falling outside of the range of pass/fail decision criteria.

5. (Currently Amended) A semiconductor testing method for testing semiconductor devices, configured to feed back data of returned samples which have been shipped as good samples, but returned from a user to a ~~manufacture~~ manufacturer as faulty samples so as to improve testing performance, the method comprising:

reading test vector data;

measuring current data of good samples and the ~~returned~~ samples returned by the user, by supplying the test vector data to the good and returned samples;

determining a range of pass/fail decision criteria and effective address pairs for testing target semiconductor devices based upon the measured current data; and

applying the test vector data for the effective address pairs to the target semiconductor devices for testing.

6. (Previously Presented) The method of claim 5, further comprising:
selecting a plurality of address pairs from the test vector data;

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

supplying the address pairs to the good samples and the returned samples;

measuring current-values of the good samples and the returned samples;

calculating changing rates of each of the good samples and the returned samples;

determining a range of pass/fail decision criteria by using the changing rates of each of the good samples;

comparing the changing rates of each of the returned samples to the range of pass/fail decision criteria;

determining whether the changing rates of each of the returned samples fall outside of the range of pass/fail decision criteria;

determining the changing rate falling outside of the range of pass/fail decision criteria; and

selecting an address pair which makes the returned samples to provide the changing rate falling outside of the range of pass/fail decision criteria as the effective address pair.

7. (Previously Presented) The method of claim 5, further comprising:
- acquiring the effective address pair;
- supplying the test vector data corresponding to the effective address pair to the target semiconductor devices;
- measuring current-value output of the target semiconductor devices;

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

calculating change rates of the target semiconductor devices; and
determining a changing rate falling outside of the range of pass/fail
decision criteria.

8. (Previously Presented) The method of claim 7, further comprising
displaying the changing rate falling outside of the range of pass/fail decision criteria on a
display.

9. (Currently Amended) A program with which a semiconductor testing
method is executed by a computer in a semiconductor testing apparatus which
comprises a read circuit, a determination circuit, an IDDQ measuring circuit configured
to test semiconductor devices by applying test vector data, configured to feed back data
of returned samples which have been shipped as good samples, but returned from a
user to a ~~manufacture~~ manufacturer as faulty samples so as to improve testing
performance, the program comprising:

instructions configured to read the test vector data;

instructions configured to supply the test vector data to good samples and
~~returned~~ the samples returned by the user;

instructions configured to measure current data of the good and returned
samples;

instructions configured to determine a range of pass/fail decision criteria
and effective address pairs for testing target semiconductor devices based upon
the measured current data; and

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

instructions configured to apply the test vector data for the effective address pairs for testing.

10. (Previously Presented) The program of claim 9, further comprising:
instructions configured to select a plurality of address pairs from the test vector data;

instructions configured to supply the address pairs to the good samples and the returned samples;

instructions configured to measure current-values of the good samples and the returned samples;

instructions configured to calculate changing rates of each of the good samples and the returned samples;

instructions configured to determine a range of pass/fail decision criteria by using the changing rates of each of the good samples;

instructions configured to compare the changing rates of each of the returned samples to the range of pass/fail decision criteria;

instructions configured to determine whether the changing rates of each samples fall outside of the range of pass/fail decision criteria;

instructions configured to determine the changing rate falling outside of the range of pass fail decision criteria; and

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

instructions configured to select an address pair that makes the returned samples to provide the changing rate falling outside of the range of pass/fail decision criteria as the effective address pair.

11. (Previously Presented) The program of claim 9, further comprising:
instructions configured to acquire the effective address pair;
instructions configured to supply the test vector data corresponding to the effective address pair to the target semiconductor devices;
instructions configured to measure current-value output of the target semiconductor devices;

instructions configured to calculate changing rates of the target semiconductor devices; and

instructions configured to determine a changing rate falling outside of the range of pass/fail decision criteria.

12. (Previously Presented) The program of claim 11, further comprising instructions configured to display the changing rate falling outside of the range of pass/fail decision criteria on a display.

13. (Currently Amended) A semiconductor testing method of specifying a faulty part in a semiconductor device, configured to feed back data of returned samples which have been shipped as good samples, but returned from a user to a ~~manufacture~~ manufacturer as faulty samples so as to improve testing performance, the method comprising:

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

reading a test program and test vector data;

supplying the test vector data to good and ~~returned~~ the samples returned
by the user;

measuring current data of the good and returned samples, employing an
IDDQ measuring circuit;

determining a range of pass/fail decision criteria and effective address
pairs for testing target semiconductor devices in a manufacturing process based
upon the measured current data;

applying the test vector data for the effective address pairs to a target
semiconductor device; and

specifying a faulty part within the target semiconductor device by
measuring an emission from the target semiconductor device.

14. (Previously Presented) The method of claim 13, further comprising:

selecting a plurality of address pairs from the test vector data;

supplying the address pairs to the good samples and the returned
samples;

measuring current-values of the good samples and returned samples;

calculating changing rates of each of the good samples and returned
samples;

determining a range of pass/fail decision criteria by using the changing
rates of each of the good samples;

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

comparing the changing rates of each of the returned samples to the range of pass/fail decision criteria;

determining whether the changing rates of each of the returned samples fall outside of the range of pass/fail decision criteria;

determining the changing rate falling outside of the range of pass/fail decision criteria; and

selecting an address pair which makes the returned samples to provide the changing rate falling outside of the range of pass/fail decision criteria as the effective address pair.

15. (Previously Presented) The method of claim 14, wherein the faulty part specifying step further comprises:

acquiring the effective address pair;

supplying the test vector data corresponding to the effective address pair to the target semiconductor device;

measuring current-value output of the target semiconductor device;

calculating changing rates of the target semiconductor device;

measuring an emission from the target semiconductor device; and

determining a changing rate falling outside of the range of pass/fail

decision criteria.

16. (Currently Amended) A semiconductor testing apparatus for specifying a faulty part in a semiconductor device, configured to feed back data of

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

returned samples which have been shipped as good samples, but returned from a user to a ~~manufacture~~ manufacturer as faulty samples so as to improve testing performance, the apparatus comprising:

a read circuit configured to read test vector data and a test program;

an IDDQ measuring circuit configured to measure current data of good samples and the ~~returned~~ samples returned by the user, by supplying the test vector data to the good and returned samples;

a determination circuit configured to determine a range of pass/fail decision criteria and effective address pairs for testing target semiconductor devices in a manufacturing process; and

a faulty part specifying circuit configured to apply the test vector data for the effective address pairs to the target semiconductor device and to specify a faulty part by measuring an emission from the target semiconductor device.

17. (Previously Presented) The method of claim 13, wherein determining a range of pass/fail decision criteria is achieved by:

a changing rate calculation circuit configured to select a plurality of address pairs from the test vector data, to supply the address pairs to the good samples and the returned samples, to measure current-values of the good samples and returned samples, and to calculate changing rates of each of the good samples and returned samples;

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

a range criteria determination circuit configured to determine a range of pass/fail decision criteria by using the changing rates of each of the good samples;

a comparing circuit configured to compare the changing rates of each of the returned samples to the range of pass/fail decision criteria, and to determine whether the changing rates of each of the returned samples fall outside of the range of pass/fail decision criteria; and

an effective address pair determination circuit configured to determine the changing rate falling outside of the range of pass/fail decision criteria, and to select an address pair that makes the returned samples to provide the changing rate falling outside of the range of pass/fail decision criteria as an effective address pair.

18. (Previously Presented) The method of claim 17, wherein the faulty part specifying circuit further comprises:

a tester configured to acquire the effective address pair, to supply the test vector data corresponding to the effective address pair to the target semiconductor device, to measure current-value output of the target semiconductor device, and to calculate changing rates of the target semiconductor device;

an emission measuring circuit configured to measure an emission from the target semiconductor device; and

Customer No. 22,852
Application No. 09/708,490
Attorney Docket No. 3180.0269-00

a decision circuit configured to determine a changing rate falling outside of the range of pass/fail decision criteria.

19. (Currently Amended) A program with which a semiconductor testing method is executed by a computer in a semiconductor testing apparatus which comprises a read circuit, a determination circuit, and a faulty part specifying circuit, configured to feed back data of returned samples which have been shipped as good samples, but returned from a user to a ~~manufacture~~ manufacturer as faulty samples so as to improve testing performance, the program comprising:

instructions configured to read a test program and test vector data;

instructions configured to measure current data of good samples and the ~~returned~~ samples returned by the user, employing an IDDQ measuring circuit, by supplying the test vector data to good and returned samples;

instructions configured to determine a range of pass/fail decision criteria and effective address pairs for testing target semiconductor devices in a manufacturing process based upon the measured data;

instructions to apply the test vector data for the effective address pairs to the target semiconductor device; and

instructions to specify a faulty part within the target semiconductor device by measuring an emission from the target semiconductor device.

FINNEGAN
HENDERSON
FARABOW
GARRETT &
DUNNER LLP

1300 I Street, NW
Washington, DC 20005
202.408.4000
Fax 202.408.4400
www.finnegan.com